

Ryutopia 【Noh Theatre】

Lighting System

Input Power Supply

Main Power Supply	3 ϕ 4W	182/105V	50Hz	60KVA	200AT	
-------------------	-------------	----------	------	-------	-------	--

Lighting Console

House Console	MARUMO Lighting Board (LB) × 1			movement type
	Channel	24		
	Memory cues	unavailable		
	Preset fader	24ch × 3lines		
	Group fader	6		
	Output	DMX512 × 1		

Circuits <100v 50Hz>

Position	Dimmer	Direct	DMX out	Notes
Downstage Garret	20A × 8			hon-butai
Upstage Garret	20A × 3			ato-za
Upstage Rightside Garret	20A × 4			hashigakari
Ceiling Position 1	20A × 2			
Ceiling Position 2	20A × 4			
Rightside Ceiling Position	20A × 4			

Extra Power Rack <100v 50Hz>

Position	3 ϕ 4w	Dimmer	Direct of others	DMX out	Notes
Stage left Backstage	100A	20A × 8	30A × 6		

Lighting equipment list

ITEM			Qty.	Position	Notes
Border light					
85w × 12-Cell	Marumo	UHQ-85W12L-4C-T1	4	Downstage Garret	Fixed
85w × 8-Cell	Marumo	UHQ-85W8L-4C-T1	1	Downstage Garret	Fixed
85w × 6-Cell	Marumo	UHQ-85W6L-3C-T1	3	Upstage Garret	Fixed
85w × 8-Cell	Marumo	UHQ-85W8L-4C-T1	6	Upstage Rightside Garret	Fixed
Profile spot light					
575w Profile	ETC	SOURCE FOUR 426	8	Ceiling Position 2	
750w Profile	Marumo	RIKURI2 36° 750W	4	Ceiling Position 1	Fixed
			4	Rightside Ceiling Position	Fixed